

EECS  
DOMAIN PROTOCOL  
FOR  
AST – LATVIA

---

Document Reference	AIB-[2026]-DP-[v3.0]- [AST] [Latvia]
Prepared by	EECS Scheme Member
Release	3.0
Date	21 January 2026
Based on EECS Rules	Release 8 v1.10

## DOCUMENT CONTROL

Version	Date	Originator	Reviewers
0.1	05.07.2020	AST	
0.2	09.08.2020	AST	
	25.08.2020	AST	
	01.10.2020	AST	
Final	05.10.2020	AST	Emma Kelly and Markus Klimscheffskij
1.1	13.01.2020	AST	Emma Kelly and Markus Klimscheffskij
2.0	09.02.2021	AST	Emma Kelly and Markus Klimscheffskij
2.1	22.07.2022	AST	Emma Kelly and Jana Vynckier (replaced by Bram Van Der Hejde)
3.0	21.01.2026	AST	Emma Kelly and Ann-Christin Austang

Version	Date	Approver	Responsibility
1.1	ESG	09.10.2020	ESG
2.0	ESG	23.02.2021	ESG
2.1	ESG	22.09.2022	ESG
3.0	ESG	21.01.2026	ESG

## CHANGE HISTORY

Version	Description
1.1	Application to become a member of the ESG
2.0	Changes to disclosure rules and small amendments/clarifications
2.1	First periodic audit after one year of operation
3	Three year periodic audit

---

 TABLE OF CONTENTS

A	Introduction.....	- 5 -
B	General .....	- 6 -
B.1	Scope .....	- 6 -
B.2	Status and Interpretation .....	- 6 -
B.3	Roles and Responsibilities .....	- 7 -
B.4	Summary: Issuance scope .....	- 8 -
C	Overview of National Legal and Regulatory Framework.....	- 9 -
C.1	Energy Market context for electricity .....	- 9 -
C.2	The EECS Framework.....	- 10 -
C.3	National Energy Source Disclosure.....	- 12 -
C.4	National Public Support Schemes .....	- 14 -
C.5	EECS Product Rules.....	- 15 -
C.6	Non-EECS certificates in the Domain .....	- 15 -
C.7	Local Deviations from the EECS Rules .....	- 15 -
D	Registration .....	- 16 -
D.1	Registration of an Account Holder .....	- 16 -
D.2	Resignation of an Account Holder.....	- 17 -
D.3	Registration of a Production Device.....	- 17 -
D.4	De-Registration of a Production Device .....	- 20 -
D.5	Maintenance of Production Device Registration Data.....	- 21 -
D.6	Audit of Registered Production Devices.....	- 22 -
D.7	Registration Error/Exception Handling .....	- 24 -
E	Certificate Systems Administration.....	- 26 -
E.1	Issuing EECS Certificates.....	- 26 -
E.2	Eligible energy for EECS Certificates.....	- 27 -
E.3	Processes .....	- 27 -
E.4	Measurement .....	- 29 -
E.5	Energy Storage .....	- 31 -
E.6	Energy Carrier Conversion.....	- 32 -
E.7	Combustion Fuel and Production Devices with multiple energy inputs .....	- 32 -
E.8	Format .....	- 33 -
E.9	Transferring EECS Certificates .....	- 36 -

---

---

E.10	Administration of Malfunctions, Corrections and Errors .....	- 37 -
E.11	End of Life of EECS Certificates – Cancellation .....	- 38 -
E.12	End of Life of EECS Certificates – Expiry .....	- 40 -
E.13	End of Life of EECS Certificates – Withdrawal .....	- 40 -
F	Issuer's Agents .....	- 41 -
F.1	Production Auditor .....	- 41 -
F.2	Production Registrar .....	- 41 -
F.3	Measurement Body(/ies) .....	- 41 -
G	Activity Reporting .....	- 42 -
G.1	Public Reports .....	- 42 -
G.2	Record Retention .....	- 42 -
G.3	Orderly Market Reporting .....	- 43 -
H	Association of Issuing Bodies .....	- 44 -
H.1	Membership .....	- 44 -
H.2	Complaints to the AIB .....	- 44 -
I	Change Control .....	- 45 -
I.1	Complaints to AST .....	- 45 -
I.2	Disputes .....	- 45 -
I.3	Change Requests .....	- 45 -
Annex 1 CONTACTS List .....		- 47 -
ANNEX 2 Account Application/Amendment Form .....		- 49 -
ANNEX 3 Production Device Registration/Amendment Form .....		- 51 -
ANNEX 4 High Efficiency cogeneration declaration .....		- 54 -
ANNEX 5 Declaration for the mixed-fuel Production Devices .....		- 55 -
ANNEX 6 Approval form .....		- 56 -
ANNEX 7 EECS Cancellation Statement .....		- 57 -
ANNEX 8 EECS GO view in the Registry .....		- 59 -

---

---

## A INTRODUCTION

This Domain Protocol describes how the EECS Standard has been implemented in a certain Domain (country/region) for a certain type of energy certificate, and it indicates where that system deviates from that standard. The EECS framework including the Domain Protocol aims to ensure robustness and transparency for all parties involved.

A Domain Protocol promotes quality and clarity, as it:

- explains local rules;
- provides clear information to all stakeholders (consumers, market parties, other members, government, the EU Commission etc.);
- facilitates assessment of compliance and permissible deviation from the EECS Rules;
- facilitates audit; and
- translates local rules into a single format and language, supporting each of the above.

Important contact information is provided in Annex 1.

## B GENERAL

### B.1 Scope

This section demonstrates compliance with the following EECS Rules:

A11.1.1	C3.1.1	E6.2.1a	E6.3.1	E6.3.2	N2.1.1	O2.1.1
---------	--------	---------	--------	--------	--------	--------

- B.1.1 This Domain Protocol sets out the procedures, rights, and obligations, which apply to the Domain of Latvia and relate to the EECS Electricity Scheme as defined in the EECS Rules.
- B.1.2 Production Device qualification for this Domain will be determined such that, the Production Device is effectively located in Latvia.
- B.1.3 AS "Augstsprieguma tīkls" (hereinafter – AST) is authorised to Issue EECS GOs relating to the following EECS Product(s):
  - EECS GO
- B.1.4 AST is authorised to Issue EECS GOs relating to the following EECS Product Type(s):
  - Source
  - Technology, implying the mandate to issue certificates for High-Efficiency Cogeneration in accordance with EU Directive 2012/27 (EU).
- B.1.5 AST is authorised to Issue EECS GOs relating to the following Energy Carriers: **electricity** and the following energy sources:
  - renewable (including biomass);
  - fossil (only for High-Efficiency Cogeneration);
  - electricity released from integrated Storage Systems (BESS).
- B.1.6 AST is not authorised to issue any energy certificates outside of the EECS Framework. There are currently no national Guarantees of Origin (GOs), quota obligation certificates, or other non-EECS certificates in operation in Latvia. All energy certificates issued by AST are EECS GOs in accordance with the EECS Rules and Latvian legislation. The following parts of this Domain Protocol do not apply for these non-EECS certificates: (such certificates do not exist in Latvia)

### B.2 Status and Interpretation

This section demonstrates compliance with the following EECS Rules:

E6.2.1d	E6.2.4	E6.3.1	E6.3.4
---------	--------	--------	--------

- B.2.1 This document refers to EECS Rules 8 version 1.10. It is based on the Domain Protocol template release *from February 2024*.
- B.2.2 The EECS Rules are subsidiary and supplementary to national legislation.

- B.2.3 The EECS Rules and its subsidiary documents are implemented in Latvia in the manner described in this Domain Protocol. Any deviations from the provisions of the EECS Rules that may have material effect are set out in section C.7 of this document.
- B.2.4 The capitalised terms used in this Domain Protocol shall have the meanings ascribed to them in the [EECS Rules](#) except as stated in section C.7 of this document.
- B.2.5 This Domain Protocol is made contractually binding between any EECS Participant and AST by agreement in the form of the Standard Terms and Conditions.
- B.2.6 In the event of a dispute, the approved English version of this Domain Protocol will take precedence over a local language version.

### B.3 Roles and Responsibilities

This section demonstrates compliance with the following EECS Rules:

A11.1.1	C3.1.1	E4.2.2	E6.2.1c	H
---------	--------	--------	---------	---

- B.3.1 The Authorised Issuing Body for EECS GOs in Latvia is AST. Its role is to administer the EECS Registration Database and its interface with the EECS Transfer System. Information regarding service fees and invoicing is available on the AST website under subsection fees: <https://www.ast.lv/en/content/guarantees-origin>.
- B.3.2 The Competent Authority for EECS GOs in Latvia is AST. Its role is defined by legislation to be responsible for the operation of for EECS GOs in Latvia.
- B.3.3 The Authorised Measurement Body Transmission and Distribution System Operators that are listed on The Public Utilities Commission website <https://www.sprk.gov.lv/content/pakalpojumu-sniedzeji-1>. They are the Authorised Measurement Bodies established under national regulation to be responsible for the collection and validation of measured volumes of energy used in national financial settlement processes.
- B.3.4 Contact details for the principal roles and Issuing Body agents are given in 0.
- B.3.5 The EECS Registration Database operated by AST can be accessed via the website <http://grex.grexel.com>.
- B.3.6 The Production Auditor is the independent accredited Production Auditor whose role is to verify and approve information which is provided from the Account Holder via Annex 3, Annex 4 and Annex 5. However, in accordance with Article 29.10, paragraph 4 of the Electricity Market Law, in cases where the installed capacity of the electricity production facility is below 50 kilowatts or where electricity is produced by an energy community, approval by a Production Auditor is not required for the completion of Annex 3. Production Auditors use industry best practices which also include on-site inspections. See section D.3.4. for details regarding audit practise.
- B.3.7 The Public Trader (hereinafter – Public Trader), purchases electricity from producers under mandatory procurement and based on Electricity Market Law, it must receive all issued EECS GOs from stations which are included in the National Support Schemes and

provide data to AST about to what extent the unit of energy has benefited from support. The Public Trader has the above mentioned right, only for the period for which Production Devices receive benefits from National Support Schemes. The benefit unit of energy is expressed in EUR/MWh. The Public Trader can also act as an Account Holder.

- B.3.8 All application forms, general information and final publication of EECS GOs operations are available on the AST website: <https://www.ast.lv/en/content/guarantees-origin>.
- B.3.9 The Account Holder is a private or legal person who has successfully completed the registration process and for whom AST has created an Account in the Registry, activated it and the applicant, has received full rights to create the root user for the Account. The Account Holder can apply for the registration of the Production Device in the Registry.
- B.3.10 Production Registrar - AST acts as the Production Registrar and is responsible for assessing applications to register Production Devices for the purposes of the relevant EECS Product and national legislation. To ensure the accuracy of the information provided, AST relies on the Production Auditor in cases where the installed capacity of the Account Holder's electricity production facility exceeds 50 kilowatts. In cases where the installed capacity is below 50 kilowatts, AST relies on the information provided by the distribution system operator. See section D.3.4. for details regarding audit practise.
- B.3.11 The Disclosure body – The Public Utilities Commission (hereinafter – the Regulator) issues disclosure rules and governs supplier disclosure statements.
- B.3.12 Residual mix calculating body – AST conducts residual mix calculations.
- B.3.13 The State Environmental Service of Republic of Latvia (hereinafter – VVD) – is the state authority overseeing the compliance of Production Devices that receive public support. In the Latvian domain it fulfils role of the Production Auditor. In cases where the installed capacity of the Production Device is below 50 kilowatts and AST relies on the data provided by the Distribution System Operator (hereinafter – DSO), the DSO fulfils the role of the Production Auditor. See section D.3.4. for details regarding audit practise.
- B.3.14 The following section(s) must be included in a Domain Protocol for each NGC that exists in the Domain and for any combination of EECS Product and ICS that can be issued.
- B.3.15 No EECS GOs in combination with a Label Scheme are issued in Latvia.
- B.3.16 There are no other Authorised Issuing Bodies for GOs in the Latvian Domain.

#### B.4 Summary: Issuance scope

- B.4.1 In summary, AST has been authorised to issue the following types of energy certificates:

Issuing Body issues certificates for Electricity		Electricity – Product Type	
	Energy Source	Source	Technology (= High-Efficiency Cogeneration)
EECS GO	Hydro	x	
	Wind	x	

	Solar	x	
	Geothermal	x	x
	Biomass	x	
	Landfill & sewage treatment plant gas	x	x
	Tidal/wave/other ocean energy	x	
	Ambient energy	x	
	Fossil		x
	Nuclear	No nuclear plants in Latvia	
<b>National GO (non-EECS*)</b>	N/A		
<b>EECS Support Certificate</b>	N/A		
<b>EECS Target Certificate</b>	N/A		
<b>EECS NGC (name)</b>	N/A		
<b>National certificate other than GO (non-EECS*)</b>	N/A		

(\*) Non-EECS certificates may not be transferred over the AIB hub.

## C OVERVIEW OF NATIONAL LEGAL AND REGULATORY FRAMEWORK

### C.1 Energy Market context for electricity

- C.1.1 The electricity market in Latvia is fully open and in line with Directive 2019/944. Wholesale trades are done Day-ahead and the Intraday market is operated by NordPool. There are also forward market energy products in Nasdaq (ENOY, EPAD) that are used for renumeration Day-ahead market results. Also possible are forward hedging opportunities, financial transmission rights on the Estonia-Latvia border issued by AST: <https://www.ast.lv/en/content/ptr-limited-auctions>.

- 
- C.1.2 Transmission and distribution system operators are fully independent from energy generation and suppliers. More detail on the Electricity market law: <https://likumi.lv/ta/en/en/id/108834>.
- C.1.3 Overview of the Latvian electricity market statistics of generation, import/export and consumption can be viewed on the AST webpage: : <https://www.ast.lv/en/electricity-market-review>.

## C.2 The EECS Framework

This section demonstrates compliance with the following EECS Rules:

<b>D3.1.2</b>	E6.2.1b	E6.2.1d	<b>N8</b>	0.10
---------------	---------	---------	-----------	------

- C.2.1 For this Domain, the relevant local enabling legislation is as follows:
- Electricity Market Law, implementing the directives 2009/72/EC, 2009/28/EC and 2018/2001 EC. Available at: <https://likumi.lv/ta/id/108834-elektroenergijas-tirgus-likums>.
  - AST has been properly appointed as an Authorised Issuing Body for RES EECS GOs and high efficiency cogeneration EECS GOs under Electricity market law Article 29<sup>2</sup> which entered into force on 1<sup>st</sup> of December 2020. Available at: <https://likumi.lv/ta/id/108834-elektroenergijas-tirgus-likums>.
- C.2.2 AST has been properly appointed as an Authorised Issuing Body for EECS GOs under Article 29.2 of the Electricity Market Law of Latvia, which came into force on 1 December 2020. Summary of the main provisions:

- 
- C.2.2.1 The Electricity Market Law specifies the details concerning the EECS GOs system in Latvia. Article 29.2 of Electricity market law states: "A guarantee of origin may be issued for the quantity of electricity produced and injected into the system operator's grid, or for the quantity of electricity produced and delivered via a direct line (the accounting of which is carried out in accordance with paragraph five of this Article), expressed in megawatt-hours (MWh). The minimum quantity of electricity for which a guarantee of origin may be issued is one megawatt-hour (MWh). No more than one guarantee of origin may be issued per unit of electricity produced, and it shall be accounted no more than once."
- C.2.2.2 The EECS GO is an electronic document issued by AST upon application of the Account holder sole purpose of the EECS GOs is to prove that the unit of electricity has been produced from a renewable source or high efficiency co-generation for electricity production.
- C.2.2.3 Any use of the EECS GOs should take place within 12 months of production of the corresponding energy unit, after this period they will expire. The EECS GOs will be cancelled in the Registry once it has been used.
- C.2.2.4 For the issuance of an EECS GO regarding electricity produced in high-efficiency co-generation units, primary energy savings will be calculated in accordance with the procedures determined by the Cabinet of Ministers on the calculation of primary energy savings of cogeneration units. Link to procedure: <https://likumi.lv/ta/id/317216-noteikumi-par-elektroenergijas-razosanu-uzraudzibu-un-cenu-noteiksanu-razojot-elektroenergiju-kogeneraciju>. The calculation of primary energy savings of cogeneration units' information will be provided by the Production Device owner and confirmed by the Production Auditor.
- C.2.2.5 The TSO shall publish information about issued EECS GOs on <http://grex.grexel.com> and its webpage <https://www.ast.lv/en/content/guarantees-origin>.
- C.2.2.6 For providing proof to a final customer that a given share or quantity of energy was produced from specific energy sources or technology type, the EECS GOs issued in Latvia or in other Member States of the European Union or in other states from European Economic Area shall be used. The EECS GOs can be transferred independently of the energy to which it relates, from one Account Holder to another.
- C.2.2.7 The amount of EECS GOs to be issued shall be determined using remote measurement devices and is calculated as the net electrical energy injected via the producer's connection points to the grid, or produced and delivered via a direct line within the territory of Latvia, during one calendar month period, described more in detail in section E.3. Measurement Bodies send electricity metering data directly AST.
- C.2.2.8 In accordance with Electricity Market law, AST can only recognize the EECS GOs issued in European Union Member States and the European Economic Area according to the EECS Rules.

### C.3 National Energy Source Disclosure

This section demonstrates compliance with the following EECS Rules:

E3.3.14			
---------	--	--	--

- C.3.1 For this Domain, the authorised body for supervision of Disclosure of the origin of energy towards consumers is Public Utilities Commission. This body is responsible for supervision of disclosure of the origin of the following Energy Carriers: electricity. In accordance with EECS Rule C7.4.1, AST, as the Scheme Member, provides the Public Utilities Commission with statistics on Cancelled Scheme Certificates for consumption in this Domain, per category as specified in EECS Rule C7.2.1(e) and (h).
- C.3.2 Disclosure rules apply uniformly across the entire territory of Latvia. There are no separate regional or island-specific rules. Supervision of disclosure is allocated to a single competent body, namely the Public Utilities Commission (PUC). The PUC ensures consistent implementation of disclosure rules across all consumption areas in Latvia.
- C.3.3 The legislation and regulation for disclosure are available at following links:
- Electricity Market Law, implementing the directives 2009/72/EC and 2009/28/EC: <https://likumi.lv/ta/id/108834-elektroenergijas-tirgus-liikums>
  - Decision No.1/16 of the Board of the Public Utilities Commission of December 3, 2020 "Rules on information to end-users of electricity and natural gas": <https://www.vestnesis.lv/op/2020/236.23>
  - Decision No.1/4 of the Board of the Public Utilities Commission of June 26, 2013 "Network code in the electricity sector": <https://likumi.lv/ta/id/257943-tikla-kodekss-elektroenergijas-nozare>
- C.3.4 Article 32 (4) of the Electricity Market Law delegates to Public Utilities Commission the authority to determine what information and to what extent the electricity suppliers have to include in the end-user bills and informational materials. While the Public Utilities Commission describes in detail the methodology and process of disclosure.
- C.3.5 Previously mentioned legislation implements the requirements arising from Article 3(9) of the Directive 2009/72/EC and additional requirements set out in Annex I of Directive 2019/944.
- C.3.6 Brief summary of the disclosure methodology and process:

- 
- C.3.6.1 The supplier shall provide to the end-consumer information, together with an invoice or with other presented information and promotional materials.
- C.3.6.2 Invoices that suppliers send to end-consumers shall provide the following information: the name of the energy product received; the amount of energy delivered during the billing period in kWh; energy price for the billing period [EUR/kWh]; energy bill during the billing period [EUR]; the cost of transmission and distribution system components [EUR]; the cost of the mandatory procurement components [EUR] (does not apply to bills for non-household users and non-delegated powers suppliers to pay for the mandatory procurement components); total payment amount for the billing period [EUR]; information on how to access detailed consumption information, information about electricity origin and environmental impact.
- C.3.6.3 At least once a year, no later than by 31st July, the electricity supplier shall provide end-consumers with informative material on the environmental impact, in terms of at least CO2 emissions and the radioactive waste resulting from the electricity produced by each product fuel mix of the supplier over the preceding year. Information should be available through information in bills
- C.3.6.4 At least once a year, not later than by 31<sup>st</sup> July, the electricity supplier shall provide the end-consumers with access to informative material (Information should be available through information in bills) for previous year which includes:
- information on the origin of the electricity supplied for the previous calendar year, indicating the share of electricity purchased from electricity producers in Latvia as a share of the total amount of electricity supplied to end-consumers;
  - the share of electricity procured from other traders in Latvia in the amount of electricity delivered to the end-users;
  - the proportion of electricity produced from each type of renewable energy (hydropower, biogas, biomass, wind energy, solar energy or other renewable energy sources) as a share of the total amount of electricity supplied to end users;
  - the proportion of electricity produced from each type of fossil fuels (natural gas, coal, shale or other fossil fuels) to the total amount of electricity supplied to end-consumers;
  - the proportion of electricity produced from an energy source (which is not mentioned previously, but appears in the AST calculated residual mix) against the total amount of electricity supplied to end-consumers.
- C.3.7 Information about the origin of supplied energy must be based on explicitly tracked electricity origin, by cancelling GOs and for untracked supplied energy share the Residual Mix must be used as described in the national regulatory provisions.
- C.3.8 According to Electricity Market law, AST has created and maintains the national Residual Mix calculation methodology. AST has adopted an Issuance based method available on the AST website under subsection residual mix: <https://www.ast.lv/en/content/guarantees-origin>. The Latvian national Residual mix is calculated by using information about national generation, consumption, issued and expired certificates, European residual mix and imported/exported energy from External

countries. Calculations are done in cooperation with AIB. On high level base formula of Residual mix:

Residual mix = Generated electricity – Issued EECS GO + Expired EECS GO + Import from external country – Export from external country ± European residual mix;

Note: External country - Country not included in the European Residual Mix calculation area

- C.3.9 The residual mix of the previous year shall be calculated and published by the 30<sup>th</sup> of June on AST website <https://www.ast.lv/en/content/guarantees-origin>.
- C.3.10 According to article 60 of Decision No.1/4 of the Board of the Public Utilities Commission of June 26, 2013 "Network code in the electricity sector" the Transmission System Operator shall have the right to request from the Distribution System Operator information associated with the issuing of EECS GOs.
- C.3.11 Cancelations for usage in another Domain (i.e. Ex Domain Cancellations) are allowed under the following restrictions: Domain allows such cancelation and (if applicable) AST has agreement with Domains competent authority. For information contact AST: go@ast.lv.

#### C.4 National Public Support Schemes

This section demonstrates compliance with the following EECS Rules:

None directly			
---------------	--	--	--

- C.4.1 Mandatory procurement is a state-approved support mechanism for electricity producers, which provides financing from electricity end-user payments. The Cabinet of Ministers has determined the criteria for the qualification of co-generation plants for acquiring this right as well as for production of electricity using renewable energy sources. The conditions for the production of electricity and the pricing procedure are regulated by the Cabinet of Ministers regulations, the purchase price of electricity is also determined by the Cabinet of Ministers. It is differentiated depending on the type of resource and power plant (Cabinet Regulation No. 560 of September 2 2020 "Regulations on Electricity Generation from Renewable Energy Sources, as well as on Pricing Procedures and Monitoring" available at: <https://likumi.lv/ta/id/317215-noteikumi-par-elektroenergijas-razosanu-izmantojot-atjaunojamos-energoresursus-ka-ari-par-cenu-noteiksanu-kartibu-un-uzraudzibu> and Cabinet Regulation No. 561 of September 2 2020 "Regulations on the Production, Monitoring and Pricing of Electricity from Cogeneration" available at: <https://likumi.lv/ta/id/317216-noteikumi-par-elektroenergijas-razosanu-uzraudzibu-un-cenu-noteiksanu-razojot-elektroenergiju-kogeneracija>.
- C.4.2 During the mandatory procurement, electricity from producers is purchased by the Public Trader at a certain price. The rights to sell the produced electricity within the framework of mandatory procurement were granted by The Ministry of Economics. The conditions for the production of electricity and the pricing procedure are regulated by the Cabinet of Ministers regulations.

- 
- C.4.3 Additionally to support the process mentioned in C.4.2 a producer who produces electricity in a co-generation plant, of which the installed capacity is greater than four megawatts may receive a guaranteed payment for electric capacity installed in the co-generation plant.
- C.4.4 Electricity Market Law states that for produced electricity, that is mandatorily procured by the Public Trader or is generated in a co-generation plant that receives a guaranteed payment for installed capacity, all issued EECS GOs should be transferred to the Public Trader. The Public Trader then uses the income from trading EECS GOs to reduce its costs of mandatory procurement and guaranteed payments for installed capacity.
- C.4.5 According to the Cabinet of Ministers regulations listed in C.4.1. all Production Devices, that receives support described in C.4.2. and C.4.4., shall be registered in the Registry and in order to enable issuance of EECS GO shall submit necessary declarations (Annex 4 and 5) for period when particular Production Device receives support – more in detail E.3.6 and E.3.7

## C.5 EECS Product Rules

This section demonstrates compliance with the following EECS Rules:

E6.2.1f	E6.2.1g		
---------	---------	--	--

- C.5.1 The EECS Product Rules as applied in Latvia are set out within sections Registration and Certificate Systems Administration of this document.
- C.5.2 In accordance with EU Directives and Latvian legislation, AST issues EECS GOs for the purpose of disclosure of electricity produced from renewable sources and electricity produced from high efficient cogeneration and for final consumer transparency.

## C.6 Non-EECS certificates in the Domain

- C.6.1 Non-Governmental Certificates do not exist in Latvia.

## C.7 Local Deviations from the EECS Rules

This section identifies those areas where there are minor differences from the EECS Rules without impacting the integrity of EECS Certificates.

## D REGISTRATION

### D.1 Registration of an Account Holder

This section demonstrates compliance with the following EECS Rules:

G2.2.1			
--------	--	--	--

- D.1.1 Any private, legal person who is not a member of the Association of Issuing Bodies, or such member's affiliate or agent, can apply to be an Account Holder in the Registry. The procedures which include all information about requested attachments for opening an account in the Registry can be found on the AST website: <https://www.ast.lv/en/content/guarantees-origin>
- D.1.2 The potential Account Holder must contract with AST under the Standard Terms and Conditions (hereinafter – STCs) which is published on the AST website: <https://www.ast.lv/en/content/guarantees-origin>
- D.1.3 The potential Account Holder who wants to sign the STCs with AST must submit a completed submission form provided in Annex 2 which is published on the AST website. AST will check all information provided by the applicant in their application against the public records, the Enterprise Register of Latvia and The Public Utilities Commission. AST will also check applicants ID or passport validity and data. AST checks if organisation or person are not included in sanction list. In case that insufficient information on company available AST can request to fill "Know your customer" survey.
- D.1.4 After receiving all documentation, including the signed STCs form, from the potential Account Holder, AST evaluates whether the application can be accepted. Handling time of properly submitted applications is 10 working days from the date of submission of the application/the additional information. Reasons for rejection may be:
  - D.1.4.1 Required documents are missing or not properly filled / signed
  - D.1.4.2 AST has doubts about the aims of the applicant.
  - D.1.5 If the application is accepted, AST creates an Account in the Registry for the applicant. When the Account is activated, a log-in authorisation Certificate will be sent via e-mail to the applicant, awarding full rights to the created Account (root user). The password to install the Certificate will be sent via SMS. The applicant organization is then an Account Holder and can start operating the Account. One Account Holder organisation can have multiple users.
  - D.1.6 AST signs both copies of the STCs, one is stored in the AST archive and the other is sent to the Account Holder. As standard, electronic signature must be used and only in cases if it is not possible hand signature may be used.
  - D.1.7 AST may hold an Account in the Latvian domain and may own a Certificate only for testing purposes, it will report such activity to the Association of Issuing Bodies.
  - D.1.8 Information regarding service fees is available on the AST website: <https://www.ast.lv/en/content/guarantees-origin>

## D.2 Resignation of an Account Holder

This section must demonstrate compliance with the following EECS Rules:

None directly			
---------------	--	--	--

- D.2.1 The Account Holder must notify AST of the intent to close their account. The effective date of closure must not be less than 30 working days from the date of receipt of the relevant information by AST. This can be done by submitting via e-mail the form provided in Annex 2 with option de-register account marked.
- D.2.2 AST will close the account as of the effective date on the request or 30 working days from the date of receipt of the application by AST whichever is later.
- D.2.3 The account must not contain any EECS GOs at the time of closure and all financial claims that AST has towards an Account Holder must be settled before the closure of the account. AST requires the Account Holder to transfer or cancel all remaining EECS GOs Certificates before closure.
- D.2.4 AST is not obligated to return already paid fees of the Account Holder.
- D.2.5 AST has the right to terminate the STC unilaterally if The Account Holder has been subject to international or national sanctions or sanctions imposed by a member state of the European Union or the North Atlantic Treaty Organization affecting significant financial and capital market interests during the performance of the Contract.

## D.3 Registration of a Production Device

This section demonstrates compliance with the following EECS Rules:

C2.1.1	C2.1.2	C2.2.4	D4.1.2	E3.3.10	E3.3.11	N6.2	O6.2
--------	--------	--------	--------	---------	---------	------	------

- D.3.1 The Account Holder can apply for registration of a Production Device in the Registry. The account where EECS GOs are to be issued must be specified in Annex 3. Production Devices must be located in Latvia. The registration form is available on the AST website: <https://www.ast.lv/en/content/guarantees-origin> (Annex 3). Information provided in the registration form in Annex 3 must, in cases where the installed capacity of the electricity production facility exceeds 50 kilowatts, be verified by an accredited Production Auditor by signing the registration form (confirmation from the Production Auditor must be obtained by the Account Holder). In cases where the installed capacity is below 50 kilowatts, AST relies on the information provided by the Distribution System Operator, against which the information submitted in the registration form is compared. The requirements and the link to the list of the Production Auditors is provided in Annex 1 which is published on the AST website <https://www.ast.lv/en/content/guarantees-origin>. Confirmation from the Production Auditor is valid for 12 months from issuing date. Production auditor VVD makes periodical audits for Production Devices that receives production support and submits to AST verified information needed for Production Device registration and information is periodically updated. Production Registrar AST checks and signs the registration form if the submitted information coincides with information

---


received from VVD, VVD information is no older than 12 months and Production Device has ceased to receive support no longer than 12 months. See section D.3.4. for details regarding audit practise.

- D.3.2 Additional documents required for registration Production Device into the Registry are:
  - D.3.2.1 A completed STCs submission form as stated in section D.1.3;
  - D.3.2.2 In case whereby the applicant or its affiliate is not the owner or sole owner of the Production Device, registration of the Production Device can be done by a third person, it must include a power of attorney signed by (other) owner(s) of the Production Device. AST checks the data included in a power of attorney against information provided in the official Enterprise Register. In case of doubt AST can request additional documents. A power of attorney is not required in the case where the Public Trader registers a Production Device, which is included in a National Support Scheme and for production of which the Public Trader is legally entitled to receive EECS GOs, even if the Public Trader is not the owner of the Production Device.
  - D.3.2.3 AST may request additional information for the registration if necessary, specifying the time limit within such information must be submitted.
  - D.3.3 Only Production Devices capable of producing electricity from renewable energy source and/or from high efficiency cogeneration technology and that are equipped with the required metering equipment can be registered in the Registry. The Account Holder must specify the authorised Measurement Bodies (the electricity grid operators) to which their Production Device is connected to in the registration form (Annex 3).
  - D.3.3.1 The Account Holder must provide documentation of auxiliaries of Production Device (if any) and grid connection diagram and metering diagram of the Production Device.
  - D.3.4 AST checks that the application fulfils the national laws, EECS Product Rules and is filled in correctly. Information is verified based on available data for AST (in cases where the installed capacity of the electricity production facility exceeds 50 kilowatts, the information in the application must be confirmed by a Production Auditor; where the installed capacity is below 50 kilowatts, AST relies on the information provided by the Distribution System Operator, against which the application data is compared). In case of doubt regarding the Production Device or when AST considers it necessary, AST can inspect the Production Device on site themselves or request an inspection by inviting the Production Auditor (more in detail in D.6). In such a case, the Production Auditor's costs shall be borne by AST.
  - D.3.5 If the Production Device satisfies both the Latvian laws and the EECS Rules, passes an inspection and if all necessary application information is gathered, AST registers the Production Device in the Registry in 10 working days from point when complete registration information is received and confirms successful registration via e-mail. Successful registration enables the issuance of EECS GOs for the Production Device from start of the month when Production Device is registered, and AST informs the Account Holder accordingly. Should the potential Account Holder fail to submit the additional information on the request of AST, or the Production Device does not comply with Latvian

---

laws or the EECS Rules, AST shall reject the application and inform the Account Holder via e-mail.

- D.3.6 After Production Device successful registration, it is assigned with a unique identifier GSRN code (accessible in the Registry). GSRN code is used for Production Device identification purposes and for Grid reference EIC (Energy Identification Codes) coding and metering point code (for DSO grid) is used. Public information relating to the Production Devices will be available in the Registry public registered Production Device list and access to full information will be available for the Account Holder (Production Device Owners or the Account Holder with Power of Attorney for Production Device) under the Account Holders profile in the Registry.
- D.3.7 Information regarding service fees is available on the AST website:  
<https://www.ast.lv/en/content/guarantees-origin>
- D.3.8 Process:



#### D.4 De-Registration of a Production Device

This section must demonstrate compliance with the following EECS Rules:

None directly		
---------------	--	--

- D.4.1 An Account Holder can apply for de-registration of a Production Device in the Registry. The effective date of de-registration must not be less than 30 working days from the date of receipt of the relevant application by AST. This can be done by (digitally) signing an

Annex 3 and send to [go@ast.lv](mailto:go@ast.lv). In this case Production Auditor signature is not needed, AST will respond to the Account Holder request within 10 working days and provide information of when the Production Device will be de-registered via e-mail.

- D.4.2 AST will update the Registry for that Production Device to show that the Production Device no longer qualifies for EECS GOs with effect as of the effective date on the request or 30 working days from the date of receipt of the application by AST, whichever is later.
- D.4.3 AST is not obligated to return already paid fees of the Account Holder. No additional fees are collected for performing the de-registering process.
- D.4.4 Where AST becomes aware that a Production Device no longer fulfils, or will no longer fulfil the qualification criteria (meaning that the actual information does not correspond to that provided in the Annex 3) the Registry record for that Production Device will be updated to show that the Production Device no longer qualifies for EECS GOs with effect from:
  - D.4.4.1 (in relation to planned changes notified in advance) the date on which such planned changes are due to come into effect or
  - D.4.4.2 (in relation to other changes) as soon as reasonably practicable after becoming aware.

## D.5 Maintenance of Production Device Registration Data

This section demonstrates compliance with the following EECS Rules:

C2.2.1	C2.2.2	C2.2.3	C2.2.5	D5.1.2
--------	--------	--------	--------	--------

- D.5.1 In case of changes after Production Device registration the Account Holder is obliged to inform AST if the information no longer corresponds to submitted information in the Production Device Application/ Amendment Form (Annex 3) provided in registration process D.3 and/or latest version visible and active in the Registry. Amendments are made when the Account holder submits via e-mail to [go@ast.lv](mailto:go@ast.lv) the signed (electronically) Application/ Amendment Form (Annex 3) with changes made and marked "Amend Production Device".
- D.5.2 Where the capacity of an existing Production Device increases for any reason, including refurbishment or enhancement of the Production Device, then in case added capacity has separate metering such additional capacity may be registered in the Registry as a separate Production Device with specified application process stated in D.3. In case added capacity doesn't have separate metering than existing Production Device information is amended by filling and submitting form available in Annex 3.
- D.5.3 Only AST can change the information in the Registry related to the Production Device. In the Registry, Production Device information revisions can be done by the Account Holder, but changes in the Registry are only made once AST approves them. The Account Holder can view the Production Device version status within the Registry, and in case of questions contact AST via e-mail: [go@ast.lv](mailto:go@ast.lv).
- D.5.4 Where AST becomes aware of a change in the Production Device Registration Data (following an inspection or otherwise), AST will evaluate the impact of the changes on the

Qualifying Criteria and respond to the Account Holder within 10 working days specifying the decision taken. AST may "lock" the Production Device in the system until the updated information is provided. The Production Device may cease to be recorded in the Registry if the PD Qualification Criteria for EECS GOs are no longer fulfilled.

- D.5.5 In order to qualify for EECS GOs the Production Device must be re-registered every 5 (five) years otherwise registration of a Production Device expires. The Account Holder must re-apply for registration for the Production Device before the expiry date. The Account Holder must provide the same documents as in section D.3. AST will thereby re-check provided application and documentation and proceed to re-register the Production Device in the Registry as of the effective date on the request or the first day of the next calendar month in which AST received the request.
- D.5.6 After Production Device ceases to receive production support described in C.4.2. and C.4.4. Production Device owner must submit the Production Device Application/ Amendment Form (Annex 3) with relevant changes in support information and changes in receiving account holder for issued EECS GOs or de-register production device. AST can use VVD information for signing the Production Device Application/ Amendment Form if changes are updated in VVD information, VVD information is not older than 12 months and Production Device has ceased to receive support no longer than 12 months. After the Public trader has done issuance for all production periods when production support was received changes are made in the Registry and Production Device owner can request issuance of EECS GOs.

## D.6 Audit of Registered Production Devices

This section demonstrates compliance with the following EECS Rules:

E3.3.7	E3.3.8	D5.1.2	
--------	--------	--------	--

- D.6.1 The period between inspections of a Production Device will not exceed 5 years.
- D.6.2 After Production Device ceases to receive production support described in C.4.2. and C.4.4. Production Device owner must submit the Production Device Application/ Amendment Form (Annex 3) with relevant changes in support information and changes in receiving account holder for issued EECS GOs or de-register production device. AST can use VVD information for signing the Production Device Application/ Amendment Form if changes are updated in VVD information, VVD information is not older than 12 months and Production Device has ceased to receive support no longer than 12 months. After the Public trader has done issuance for all production periods when production support was received changes are made in the Registry and Production Device owner can request issuance of EECS GOs.
- D.6.3 If the Audit identifies material differences from the details recorded in the Registry, the Account Holder must re-apply for registration of the Production Device and EECS GOs will not be issued for respective Production Device before corrective actions have been performed.

- 
- D.6.4 Inspections verify that the Measurement Devices are correctly positioned in order to measure the quantity needed for calculating the amount of EECS GOs to be Issued.
- D.6.5 Inspections confirm the accuracy of the Measurement Devices involved in the calculation of the amount of EECS GOs to be Issued to be acceptable in accordance with the existing regulatory framework and applicable standards.
- D.6.6 Inspections confirm that the formula for calculating the amount of EECS GOs correctly reflects the amount of electricity injected into the grid via the producer's connection points, or produced and delivered via a direct line, in accordance with the principles for determining the quantity of electricity qualifying for the issuance of these EECS GOs.
- D.6.7 Audit of registration information is done by the Production Auditor who is independent of the owner or the Account Holder of the Production Device. This is a precondition for registration of Production Devices in the Registry.
- D.6.8 The Account Holder is at all times responsible for the information provided to AST and the Account Holder must ensure that the relevant information in forms Annex 3, Annex 4 and Annex 5 provided to AST is confirmed by the Production Auditor.
- D.6.9 The Account Holder is responsible at all times for reporting changes to the respective Production Device, approved to receive EECS GOs, to AST and to the relevant Authorised Measurement Body.
- D.6.10 When performing the verification of data indicated in the Declaration of a Mixed Energy Sources Production Unit or the High-Efficiency Cogeneration Declaration, auditor operates in accordance with the procedure developed approved by the accreditation body LATAK. The procedure is based on the Electricity Market Law, the guidelines of the Association of Issuing Bodies, including the domain protocol of the European energy certification system for electricity and related binding documents, as well as in compliance with the standard LVS EN ISO/IEC 17020:2012 "Conformity Assessment – Requirements for the Operation of Various Types of Bodies Performing Inspection" (ISO/IEC 17020:2012).
- D.6.11 Production Devices, that produce electricity from high efficient cogeneration must provide the Production Auditor with confirmation of declarations (declarations form available at Annex 4) in the case of requesting EECS GOs. For calculation of input parameters (Primary Energy Savings, Overall Primary Energy Savings, CO<sub>2</sub> Saved, CO<sub>2</sub> Emissions) the AIB Cogeneration model must be used.
- D.6.12 Production Devices, that use more than one energy source (multi-fuel) for producing electricity (for example sewage gas and agricultural gas), must provide the Production Auditor confirmation for declaration (declaration form available at Annex 5) in the case of requesting EECS GOs issuing.
- D.6.13 The verification and inspection process for declarations referred to in D.6.11 and D.6.12 is as follows:
- Information from the electricity producer is received regarding the need for verification, and communication with the client is established concerning the inspection visit;

- The inspection visit is always scheduled and carried out during the approval of the registration form data and at least once a year during the approval of the relevant declaration;
  - Other LATAK accredited auditor inspections/audits may also be conducted at production units, such as ISO certification audits, CHP annual report inspections, CO<sub>2</sub> verifications, etc. Production units may therefore be visited multiple times a year in different contexts, but core aspects—such as responsibilities, production flows, procedures, data recording systems, handling of missing data, instrument calibration/verification, and mass balance—are always reviewed;
  - The production unit is required to provide additional documentation, including a completed declaration, data from the recording system (e.g., consumed fuel, electricity received from the grid, produced electricity and/or heat, electricity delivered to the grid) for the relevant period, and other supplementary information as needed, such as laboratory tests on calorific value. This typically includes production records, delivery notes and invoices, laboratory test reports, acts, instrument data, and certificates of performed verifications, etc;
  - Subsequently, data analysis and aggregation are performed, with recalculations according to formulas, including those included in the binding regulations.
  - If the evaluated data match the data indicated in the declaration, an inspection report is prepared, and the declaration is approved;
  - If discrepancies in the data are identified, communication with the production unit follows, along with data correction or the request for additional information.
- D.6.14 If a new or updated Production Device Application/Amendment Form (Annex 3) is submitted at any time with a valid Auditor's signature, the inspection interval described in D.6.1 shall be reset. This means that the 5-year period between inspections will recommence from the first day of the month in which the latest submission was received.

## D.7 Registration Error/Exception Handling

This section demonstrates compliance with the following EECS Rules:

C2.2.2	E4.2.7		
--------	--------	--	--

- D.7.1 Any errors in EECS GOs resulting from an error in the registered data of a Production Device will be handled in accordance with section E.10.
- D.7.2 AST can check at any time a Production Device that generates electricity from a renewable source or high efficient cogeneration, to determine whether the electricity is generated from a renewable energy source and whether the measurement of the produced (whether injected into the grid via the producer's connection points or delivered via a direct line) electricity and EECS Domain Protocol other measures necessary for the production from renewable energy sources as mentioned in the application file, corresponds with reality by performing unplanned audit described in D.6.1.

- 
- D.7.3 Where AST determines that the Account Holder is in breach of the Product Rules or determines that a Production Device does not meet Production Device Qualification Criteria for an EECS Product in relation to which it is registered, AST shall take such action as is necessary (by informing the Account Holder) to ensure that it is compliant with the EECS Rule's section E3.3.9(b), such action include, in the case of material non-compliance by the Account Holder, the withdrawal of registration of the relevant Production Device for the purposes of that EECS Product.
  - D.7.4 AST informs AIB of such a breach if it could affect the transfer of EECS GOs out of the Registry into the Latvian Registry into the EECS Registration Database of another Member.

## E CERTIFICATE SYSTEMS ADMINISTRATION

### E.1 Issuing EECS Certificates

This section demonstrates compliance with the following EECS Rules:

A2.1.1	A2.1.2	C3.1.1	C3.2.1	C3.3.1
C3.4.2	C3.4.4	E3.3.10	N3.1.1	O3.1.1

- E.1.1 In accordance with section B.1.4, the EECS GO is the only official EECS product in Latvia. Alteration of EECS GOs is not possible, as the system and all entries are under the responsibility of AST.
- E.1.2 Only Production Devices registered in the Registry and that are connected to Distribution System Operator or Transmission System Operator grid are allowed to request EECS GOs. If the Production Device is not in the Registry, AST has no information of the Production Device or its metering, it is impossible to issue EECS GOs. Metering of Production output are done by the Authorised Measurement Bodies (more in E.3).
- E.1.3 An EECS GO shall be issued for each unit of electricity produced from renewable energy sources or high-efficiency cogeneration and either injected into the electricity grid via the producer's connection points or delivered via a direct line. Also, in the case of high-efficient cogeneration from renewable energy sources, only one EECS-GO will be issued. The face value of one (1) EECS GO is one (1) MWh. Any identifiable residual kWh will be carried forward to the next issuing period until one MWh is reached. No more than one EECS GO shall be issued per unit of electricity produced from renewable energy sources, i.e. each energy unit shall be considered only once. EECS GO shall be issued only for Production Devices fulfilling qualification criteria described in section D.3. and for output fulfilling measurement criteria described in section E.3
- E.1.4 EECS GOs are issued for the total net amount of electricity produced by the Production Device and supplied to the network in Latvia during one calendar month period. Account holders can request for EECS GO issuance up until 12 months from the production period end date. EECS GOs are then issued with a shorter expiry period which correspond to end of respective production output (month).
- E.1.5 In case a Production Device includes an integrated Battery Energy Storage System (BESS), EECS GOs may be issued for the net amount of electricity – the difference between electricity received from and injected into the grid during the same calendar month. The input energy must be demonstrably renewable and either uncertified or cancelled. No GOs are issued for the energy used to charge the battery. The GOs issued for BESS discharge inherit the attributes of the original renewable energy source.
- E.1.6 GOs issued for electricity production that take place before AST is an official AIB member are prevented from export through the AIB Hub as they are not classified as EECS GOs and may not be converted to an EECS GOs.
- E.1.7 AST will not issue EECS GOs to an Account Holder which is in debt to AST for unpaid invoices at the time the EECS GO is requested to be issued.

- E.1.8 Issued EECS GOs are by default sent to Account Holders default Transferable account. Transferable accounts can be changed in the Registry.

## E.2 Eligible energy for EECS Certificates

This section demonstrates compliance with the following EECS Rules:

N6.4	O6.4		
------	------	--	--

- E.2.1 EECS Certificates are not issued in respect of electricity consumed by production auxiliaries.

## E.3 Processes

This section demonstrates compliance with the following EECS Rules:


A.4	C3.4.1	C3.4.3	C3.5.1	C3.5.2
C3.5.3	C4.1.1	C4.1.3	D7.1.2	E.2
N6.4.	O6.4			

- E.3.1 The Account Holder of a Transferables Account should be treated (as between the Account Holder and that Member) as the owner of the EECS GOs.
- E.3.2 AST shall ensure that its manual and automated information systems for the Issue, holding and transfer of EECS GOs are able to support audit of all transactions with respect to EECS GOs.
- E.3.3 AST shall use in connection with its EECS Scheme the EECS Registration Database and Transfer Links approved for the purposes of its EECS Scheme.
- E.3.4 The Account Holder should request issuance of EECS GOs in the Registry. Request of issuance for the Account Holder is possible through the Registry, where the Account Holder can see if the metering data of the net electrical energy injected into grid or delivered via a direct line for the Production Device is available and then request the issuance of EECS GOs or send electronically signed letter with request document where is listed Production Device GSRN number, name of Production Device, production period, requested EECS GO product type and amount to be issued
- E.3.5 In the case of high efficient cogeneration stations, the Account Holder fills out a declaration (Annex 4) and in the case of (multifuel) Production Devices, the Account Holder fills out a declaration (Annex 5) for issuance of EECS GOs from the respective production output period. For calculation of input parameters (Primary Energy Savings, Overall Primary Energy Savings, CO<sub>2</sub> Saved, CO<sub>2</sub> Emissions) the AIB Cogeneration model must be used. Declarations should be submitted monthly, for monthly issuance. It is possible to submit information in a single declaration (data should still be monthly) for multiple months, if issuance is requested for multiple production periods (expiry period is set from production period end not issuance date). Declarations must be accurate and reliable and confirmed by the Production Auditor otherwise AST will reject the request

---

regarding the issuance of EECS GOs. If AST deems it sufficient, the Account Holder can provide a comparable Production Auditor confirmation to confirm the information the Account Holder provides in its declarations (Annex 4 and Annex 5). If some of the necessary information in the initial audit is missing, the Account Holder must provide the Production Auditor with confirmation of the missing items. In the case of if the Account Holder represents more than one Production Device, AST has the right on the basis of a mutual agreement to offer a different approach regarding receiving the data required in Annex 4 and Annex 5.

- E.3.6 EECS GOs are issued for the monthly total net amount of electricity produced by a registered Production Device and supplied to the network in Latvia.
- E.3.7 No later than 10 working days at the end of a calendar month the Authorised Measurement Bodies shall provide AST with information on the quantity of electricity (MWh) produced and injected into the grid or delivered via a direct line the past calendar month, by each Production Device connected into their respective grids.
- E.3.8 E.2.5. No later than within 10 working days after the end of a calendar month the Public Trader shall provide, in a format which has been agreed between AST and the Public Trader, information regarding what the Production Devices have received in capacity or energy production support for the previous month. When requesting for issuance the Public Trader will provide the extent the unit of energy has benefited in the related production period (month). Information will be entered manually into Grexel system as part of the issuance process
- E.3.9 In case of any doubts about the accuracy of meter readings and all declarations or National Support schemes, AST will not issue EECS GOs for that Production Device, it immediately stops the issuance for the Production Device until such doubts are resolved. After this AST contacts the Account Holder to find out if the discrepancy can be resolved. Issuance may only be done when discrepancies have been resolved.
- E.3.10 AST will issue the EECS GOs in the Registry only after receiving data mentioned in E.3.5; E.3.7;E.3.8., Any identifiable residual kWh will be carried forward to the next issuing period until one MWh is reached. No more than one EECS GOs shall be issued per unit of electricity produced, i.e. each energy unit shall be considered only once
- E.3.11 In normal situation, EECS GOs issuing will take no longer than 8 working days from the initial request for issuance or from the point in time when all information listed in E.3.10. is received. In cases issuance request exceeds 320 unique requests (unique request consist of request for one Production Device in one production period) then issuing process can take proportionally longer period (example, 9 days for 360 unique requests).
- E.3.12 The Account Holder shall receive information in the Registry of the issuance of EECS GOs into the Account Holder's Transferable Account and the EECS GOs details.
- E.3.13 The EECS GOs which will be issued for Production Devices based on the Public Trader request will be transferred to the Public Trader account based on C.4.5.



\* The Producer is the generic term for the party which requests certificates, and might include production aggregators, portfolio managers etc.

## E.4 Measurement

This section demonstrates compliance with the following EECS Rules:

D6.1.2	N6.4.	O6.4	
--------	-------	------	--

- E.4.1 Electricity metering equipment must be installed by the system operator on the grid border. The metering equipment must record the electricity received from the grid and the electricity injected into the grid or delivered via a direct line.. The installed electricity equipment must conform to the requirements laid down in the laws and regulations regarding the procedures for performing approval, primary verification and market supervision of the type of means of measurement, as well as in the laws and regulations regarding metrological requirements for means of measurement and regarding

metrological requirements. The system operators are responsible for a periodic verification of the electricity metering equipment. National Law On Uniformity of Measurements: <https://likumi.lv/ta/en/en/id/42562-on-uniformity-of-measurements>.

- E.4.2 Only Production Devices that are equipped with the required metering equipment shall be registered. Production Device metering equipment is located between the Production Device and transmission/distribution grid and from measurement device is possible to get both monthly aggregated data and 15-minute interval data. It is mandatory to have measuring equipment located at frontier points between the activities of generation, transmission and distribution. Measurement points to be assigned for Production Device are submitted via Production Device registration form (see D.3) by owner or its authorised representative. Measurement Bodies send electricity metering data directly to AST based on an agreed format between AST and the Measurement Bodies.
- E.4.3 The electricity is measured using the electricity meters, which record power transmission at intervals of at least 15 minutes . All electric meters should be automated and be read automatically via PLC, GPRS connection or over the Internet. System operators shall compile and transmit to the AST the monthly electricity production data of each Production Device.
- E.4.4 The Authorised Measurement Bodies (the electricity grid operators) who owns the electricity meter equipment are responsible for the measurement equipment, which shall comply with the requirements of Latvian law relating to periodical metrological control and testing, and for the measured data validation
- E.4.5 The Account Holder is responsible for the all non-electrical measurement equipment (if such data are necessary), which shall comply with the requirements of Latvian law relating to periodical metrological control and testing. This data shall be approved by the Production Auditor
- E.4.6 Before the issuance of EECS GO for a multi-fuel Production Device the Account Holder must (electronically) submit to AST a completed multi-fuel declaration form (Annex 5) which has been confirmed by the Production Auditor (or comparable audit results completed by a Production Auditor, if AST deems it sufficient (see E.4.5)). The proportion declared in Annex 5 in the case of combustible fuels should be calculated according to E.7. AST then issues EECS GOs according to the input fuel proportion factors, considering production declarations (Annex 5) and total net electricity produced from the measurement data sent by the Authorised Measurement Bodies. According to national legislation stated in C.4.1 Production Devices receiving production support (if applicable) must submit a multi-fuel declaration form 5 months after production period start for the Public trader to request issuance of EECS GOs. Each month until 10th day of the month AST informs VVD with list of Production Devices that breaches this rule
- E.4.7 In accordance to metering data and metering scheme AST estimates the net electrical energy injected into grid for each Production Device:

- E.4.7.1 In case Production Device have only one metering point, net electrical energy injected into grid equals energy injected into grid for that metering point in corresponding production period.
- E.4.7.2 In case Production device has multiple metering points (including metering solely for self consumption), net electrical energy injected into grid is calculated for each 15 min interval. From total energy injected into grid all energy received from grid in all metering points in particular 15 min interval is subtracted. In 15 min interval when energy received is larger than energy injected into grid net electrical energy injected into grid for that 15 min interval is set to 0. 15 min net electrical energy injected into grid values are aggregated to get net electrical energy injected into grid for production period (month).
- E.4.7.3 In case Production Device has multiple metering points (including metering solely for self consumption), but net electrical energy injected into grid should be calculated differently as in E.3.8.2. Production Device owner or its appointed representative submits AST methodology (i.e. calculation equations and logic) on how to perform calculation of net electrical energy injected into grid and information why it should be different. Submitted methodology must be approved by Production auditor
- E.4.7.4 In case the Production Device includes an integrated Battery Energy Storage System (BESS), the net electrical energy injected into the grid shall be calculated based on 15-minute interval data provided by the Distribution System Operator (DSO). The net value shall be calculated as the total electricity injected into the grid minus the total electricity received from the grid during the same calendar month. This net value shall be used for EECS GO issuance, provided the input energy is demonstrably renewable.
- E.4.7.5 No arrangements applied to estimate and/or adjust line losses in meter readings.

## E.5 Energy Storage

This section demonstrates compliance with the following EECS Rules:

<b>N6.4.4</b>	<b>N6.4.5</b>	<b>C3.2.4</b>	<b>C3.2.2</b>	<b>C3.6</b>
---------------	---------------	---------------	---------------	-------------

- E.5.1 EECS GOs are only issued for the output of an energy storage device under the following conditions:

- E.5.1.1 The energy used for charging the storage device originates from the same site;
- E.5.1.2 No EECS GOs have been issued for the energy that flows into the storage device;
- E.5.1.3 The Battery Energy Storage System (BESS) is exclusively connected to a single Production Unit. Energy discharged from the battery will carry the same origin class as the connected Production Unit. EECS GO issuance is not permitted where the BESS is linked to multiple Production Units.
- E.5.1.4 EECS GOs for volumes including BESS are only issued for periods starting from the date when the Production Auditor has electronically signed the production unit form confirming the existence and compliance of the BESS. EECS GOs for previous periods, during which BESS was in operation but had not yet been audited and confirmed by the Production Auditor, will not be issued retroactively.
- E.5.2 The calculation of net generation with integrated BESS shall follow the methodology described in E.4.7.4.
- E.5.3 Submitting a Production Declaration in relation to a Production Device, for which one of the inputs is stored energy, shall be obliged to submit, in respect of the same period as that to which the Production Declaration relates, a Consumption Declaration and to specify therein the amount of Output consumed in placing energy (in any medium) into storage for use by that Production Device in that period.
- E.5.4 There are no pumped storage facilities in Latvia.
- E.5.5 No arrangements applied to estimate and/or adjust line losses in meter readings.

## **E.6 Energy Carrier Conversion**

This section demonstrates compliance with the following EECS Rules:

<b>C3.2.2</b>	C3.5.4(u)	<b>C3.6</b>	
---------------	-----------	-------------	--

- E.6.1 There are currently no energy carrier conversion (as there are no GOs other than for electricity), pumped storage systems in Latvia. If such Production Devices were introduced to the grid, this Domain Protocol would be updated to reflect such a change.

## **E.7 Combustion Fuel and Production Devices with multiple energy inputs**

This section demonstrates compliance with the following EECS Rules:

<b>N6.3.2</b>	O6.3.2		
---------------	--------	--	--

- E.7.1 For a Production Device reporting the total production with multiple energy sources, the Account Holder will have to report in detail on the input factors and provide verification of the declaration from the Production Auditor prior to issuing of EECS GOs. The standard calculation set out in the EECS Rules section N6.3.2 is applied. The template of a production/consumption declaration can be found in Annex 5.

- E.7.2 All combustible fuel inputs (where needed) are separately measured and required to be submitted by the Account Holders in tonnes or 1000 m<sup>3</sup> and the lower calorific values of the fuels in MJ/kg or in MJ/m<sup>3</sup>.
- E.7.1 In a Consumption Declaration (Annex 5) for each combustible Input, the following must be specified:
- E.7.1.1 The values of M<sub>1</sub>, C<sub>1</sub>.... M<sub>n</sub> and C<sub>n</sub>; and
  - E.7.1.2 as the Energy Input Factor for that Input and that period, a factor no greater than L, where L is the proportion of the total Output produced during this period by the relevant Input and is calculated as follows:

$$L = \frac{M^1 \times C^1}{(M^1 \times C^1) + (M^n \times C^n)}$$

Where,

M<sub>1</sub> - is the mass of the relevant Energy Input for that Production Device during the relevant period

C<sub>1</sub> - is the average calorific value of the relevant Energy Input for that Production Device during the relevant period

M<sub>n</sub> - is the mass of each relevant Input other than the relevant Input for that Production Device during the relevant period

C<sub>n</sub> - is the average calorific value of each relevant Input other than the relevant Input for that Production Device during the relevant period.

## E.8 Format

This section demonstrates compliance with the following EECS Rules:

C3.5.4	C3.5.5	N6.5	N6.6	O7
O8	C3.4.4	E3.3.10	N3.1.1	O3.1.1

- E.8.1 EECS GOs shall be Issued in such format as may be determined by AIB.
- E.8.2 The following information is recorded on the EECS GOs (in relation with the optional fields mentioned in EECS C3.5.5, N6.6, O8, procedures are in place to determine the value recorded on the EECS GOs:

Subject	Name of data field on EECS Certificate	Present on issued certificates? <i>Yes (always) / No / On Request of Producer</i>	Procedure to determine the value of this data field	Reference in EECS Rules

<b>Element of Production Device</b>	Capacity of production element (in addition to nominal capacity of Production Device)	Yes	N/A	C3.5.5 a / O8.1.1
	Date operational of production element (in addition to data operational of Production Device)	Yes	N/A	C3.5.5 a
	Type of production element	Yes		C3.5.5 a
<b>Carbon footprint</b>	Quantification of Carbon Footprint (CFP)	No		C3.5.5 b
	Reference to methodology for determining the CFP	No		C3.5.5 b
<b>Production Time interval indicators</b>	Starting time when the Output was produced	Yes	According to the HubCom standard	C3.5.5 c
	End time when the Output was produced	Yes	According to the HubCom standard	C3.5.5 d
<b>Nuclear energy</b>	Quantification of radioactive waste produced per MWh of Output	N/A	N/A	C3.5.5 e
	Reference to methodology for determining the radioactive waste produced	N/A	N/A	C3.5.5 a
<b>Energy Savings [on HEC Certificates]</b>	Amount of primary energy saved in MJ/MWh	Yes		N6.6.1 b
	Primary energy savings as % of input and output flows of Cogeneration unit	Yes		N6.6.1 b

<b>GHG savings</b>	GHG emissions saved	Yes		O8.1.1 b
	Method for GHG savings	No		O8.1.1 c
	RED GHG saving criteria met Y/N	No		O8.1.1 c
<b>Sustainability criteria</b>	Sustainability criteria met Y/N, legislative requirement reference, certification scheme, certification body, reference to certificate(s)/PoS	No		O8.1.1 d
<b>Calorific value</b>	Calorific value for calculating MWh of Output	Yes		O8.1.1 e
<b>End-use of gas</b>	Category from Fact sheet End-Use of Gas (only if cancellation is restricted to this end-use)	N/A	N/A	O8.1.1 f
<b>Source-shares</b>	Info on the Inputs, their Source Type, their share in total energy Input	N/A	N/A	O8.1.1 g
<b>Pre-conversion support</b>	In case of Conversion Issuance, Indication of public support granted in relation with energy fed into converting Production Device	N/A	N/A	O8.1.1 i
<b>Composition Purity</b>	Indication of the purity of the composition of the Type of Gas	N/A	N/A	O8.1.1 j
<b>Composition criteria</b>	Reference to criteria to which	N/A	N/A	O8.1.1 k

	the gas composition complies			
<b>Advanced Biomass Feedstock</b>	Y/N	N/A	N/A	08.1.1

[Where applicable: Any other information on the EECS GOs [that is optional in accordance with EECS Rules C3.5.5, N6.6, O8]: [...]]

- E.8.3 EECS GOs and the information contained in it, or to be indicated by it, shall be in the format specified in the Subsidiary Document "HubCom".
- E.8.4 According to the National law for fossil fuel generation, in addition to requirements stated in the EECS rules, EECS GOs must contain the quantity of thermal energy produced at the same time as electrical energy and nominal efficiency of the electrical and thermal energy production of the cogeneration Production Device.
- E.8.5 No radioactive waste information is foreseen for EECS GOs issued Latvian Domain, currently there are no Nuclear generation stations and according to the National law there is no mandate to issue EECS GOs from nuclear generation, in case of changes the Domain Protocol will be updated.

## E.9 Transferring EECS Certificates

This section demonstrates compliance with the following EECS Rules:

<b>C5.1.1</b>	<b>C5.1.3</b>	<b>C5.1.6</b>	
---------------	---------------	---------------	--

- E.9.1 An Account Holder will get secure electronic access to their Account as stated in section D.1.5 to make transfers of EECS GOs to another Account in the Registry or to another EECS Registration Database in another Domain through the AIB Hub.
- E.9.2 Only persons duly authorized by the Account Holder may request the transfer of EECS GOs from that Account Holder's Transferable Account. Authorized persons must be identified on the account application form (Annex 2). Authorized persons can also be added by the root user(s) of that Account Holder.
- E.9.3 In accordance with Latvian law, from Latvia EECS GO Registry there can be sent only GOs that fulfils EECS GOs requirements and can be received only EECS GO compatible certificates, issued in the European Union Member States and the European Economic Area.
- E.9.4 The initiation of transfers is done in the Registry by the selling Account Holder. The transfer form shall be filled out by the selling Account Holder (whether it is the Producer itself or an Account Holder with power of attorney) containing the following data:
  - E.9.4.1 The amount of EECS GOs to be transferred;

- E.9.4.2 Domain of the receiving Account Holder;
- E.9.4.3 Receiving Account Holder.
- E.9.5 The transfer of EECS GOs and the confirmation of that transfer is automated. After the Account Holder has initiated the transfer, the Registry instantly displays a message of whether or not the initiation has been successful. The EECS GOs are automatically transferred to the receiving account if the initiation of the transfer is successful. If the initiation of the transfer is not successful, the EECS GOs do not leave the Account of the original Account Holder. In transfers between Accounts located in different Registries, the success of the transfer is subject to the verification process of the AIB Hub and the receiving Registry. When EECS GOs are in transit they are not available for another transfer. If the transfer is not successful, the EECS GOs return to the Account of the original Account Holder.
- E.9.6 EECS GOs that have been cancelled or expired are not available for transfer.
- E.9.7 Once an EECS GOs has been held in the registry of a non-Hub User, it may not be transferred through the Hub. AST is only allowed to use the Hub when transferring EECS GOs to another Hub User, excluding other means of transfer or separate arrangements in this respect.
- E.9.8 Ex-domain exports are handled as cancellations, where the beneficiary of the cancellation is located in another Domain or country, that is not connected with AIB HUB and respective Issuing body has signed agreement with AST for ex-domain export/import, is such agreement is needed.
- E.9.9 Ex-domain imports are handled outside the Registry for EECS GOs (see also E.11.2), information about imports of EECS compliant GOs is saved in separate database. Ex-domain imports are allowed if Domain or country is not connected with AIB HUB and respective Issuing body has signed agreement (AIB standard agreement form to be used) with AST for ex-domain export/import.
- E.9.10 There are no restrictions for transfer via AIB HUB of EECS GOs – all energy carriers and certificate types allowed.

## E.10 Administration of Malfunctions, Corrections and Errors

This section demonstrates compliance with the following EECS Rules:

C5.1.7	C8.4.1	C8.4.2	C8.4.3	C8.5.1
D9.1.2				

- E.10.1 Once issued, the details of an EECS GOs cannot be altered or deleted except to correct an error.
- E.10.2 AST has the right to perform corrective actions such as the transfer of EECS GOs in the Registry where EECS GOs have been erroneously transferred.

- E.10.3 AST has the right to perform corrective actions such as the withdrawal of EECS GOs from an Account in the Registry where EECS GOs have been erroneously issued. AST has the right to recover the cost of securing the agreement of another Account Holder to the Withdrawal of EECS certificates of the same type from that other Account Holder's Transferables Account, where the EECS GO is not in the Transferables Account of that Account Holder, so that, as far as reasonably practicable, EECS GOs are withdrawn with an amount and a financial value which make good the discrepancy.
- E.10.4 AST has the right to correct an account number for an incoming transaction if the account number is not a transferable account number and correct account number can be identified.
- E.10.5 If an error occurs in the measurement data on which EECS GOs are created, AST will correct this error. If EECS GOs are wrongly issued, i.e. a larger quantity, and traded, the error will be corrected in future, issuing a smaller amount of EECS GOs in the next period.
- E.10.6 Where it is impossible to transfer for technical reasons, this can be overcome by cancelling EECS GOs for use in another domain, subject to an agreement between AST and the importing Issuing Body.
- E.10.7 AST shall correct all errors in or with respect to the EECS GOs in question provided that such EECS GOs have not been transferred out of that Transferable Account.
- E.10.8 AST may alter an EECS GO held in its Registry so as to rectify an error which occurred prior to its transfer into the Account in which it is held at such time, provided:
- a) the Account Holder has agreed to such alteration;
  - b) it is reasonably satisfied that any unjust enrichment of an EECS Market Participant as a consequence of such error has, to the extent reasonably practicable, been nullified; and
  - c) it is reasonably satisfied that the alteration itself does not give rise to undue enrichment of the Account Holder.
- E.10.1 In the case where the EECS GOs are no longer in the Latvian domain, or in the case where erroneous EECS GOs are transferred to the Latvian domain from another Domain, AST will cooperate with other Issuing Bodies to withdraw or correct the erroneous EECS GOs.
- E.10.2 An Account Holder or market participant involved in a transaction with an Account Holder from the Latvia Domain can report an issue by submitting identified malfunctions, errors or requested corrections via e-mail to go@ast.lv. If possible, AST will resolve the issue in 5 working days and inform the Account Holder of the resolution. If the issue can not be resolved within 5 working days AST, will respond to the e-mail to inform how this issue will be tackled and the estimated time to resolve it.

## E.11 End of Life of EECS Certificates – Cancellation

This section demonstrates compliance with the following EECS Rules:

C5.2.3	C6.1.1	C7.1.1	C7.2.1	C7.2.2
C7.2.3	C7.3.1	E3.3.10	N3.1.1	O3.1.1
C7.1.3				

- 
- E.11.1 Cancellation is removing a EECS GOs from circulation. Once Cancelled, a EECS GOs cannot be moved to any other account and so is no longer tradable (transferable). Expired EECS GOs are not valid for cancellation.
- E.11.2 Cancellation of EECS Certificates is allowed for the categories of certificates, marked with X in the table below, and informing on the actor who is allowed to cancel EECS GOS:

Cancellation category	Electricity	Energy Gas	Hydrogen
End-use of energy	X		
Conversion Issuance (EECS C3.2.2 b)			
Storage Issuance (EECS C3.2.4 a.ii)	X		

- E.11.3 EECS GOs can be cancelled for use in the Latvian domain. Cancellation can be made for consumption for previous year up to 1<sup>st</sup> April in current year and cancellations for future use can be made only for consumption in current year.
- E.11.4 EECS GOs may be cancelled for use in other EECS GOs Domains provided that the transfer of such EECS GOs is not possible to the other Domain, and there is a Cancellation Agreement in place with the Scheme Member of that other Domain. Such Cancellation Agreements require the provision by the Cancelling Scheme Member to the Scheme Member of the other Domain of statistical information concerning Cancelled EECS GOs and the inclusion on any related Cancellation Statement of the identity of the Domain, Account Holder and purpose for which the EECS GOs were Cancelled.
- E.11.5 EECS GO can be cancelled for use in countries that are not connected to AIB Hub via ex-domain cancellations.
- E.11.6 Account Holders possessing EECS GOs in the Registry, can perform cancellations by executing the transaction in the Registry. The Account Holder must specify the EECS GOs to be cancelled as well as the country of consumption, cancellation purpose, usage category, name, type and location of beneficiary and related consumption period. The Account Holder may choose to cancel part of or all of a given certificate bundle or several bundles.
- E.11.7 The cancellation of EECS GOs is automated using the cancellation functionality in the Registry. An EECS GOs can only be cancelled once and when the EECS GOs has been cancelled it is taken out of circulation and is not available for transactions. Cancelled EECS GOs are removed from the transferable account by changing their status to "cancelled"; they do not appear in any Account of the Registry after the Cancellation. The Account Holder performing the cancellation has full access to see the details of the cancellation process in the Registry or they can order an official Cancellation Statement from AST (Annex 7).
- E.11.8 Having performed a cancellation, the Account Holder receives confirmation of a successful or failed cancellation process instantly in the Registry.

- E.11.9 Each month AST will provide the Secretary General with a statement of the number of EECS GOs cancelled under the provisions EECS rules C7.1.2 and E.9.4.
- E.11.10 Eligible for cancellation are only EECS GOs from renewable sources or high efficiency cogeneration type.
- E.11.11 Account Holders can request for EECS GO issuance up to 12 months from the production period end date. EECS GO are then issued with a shorter expiry period which correspond to end of respective production output (month).

### **E.12 End of Life of EECS Certificates – Expiry**

This section demonstrates compliance with the following EECS Rules:

<b>C5.2.3</b>	<b>C6.1.1c</b>	<b>E6.2.1h</b>	
---------------	----------------	----------------	--

- E.12.1 EECS GOs expire 12 months after the end of the related production period for the relevant energy unit. This means that for example an EECS GO issued for production of January 2021 shall expire on the 31st of January 2022.
- E.12.2 EECS GOs which have expired are no longer valid for transfer or any other operation. The expiry-warning period is set to 30 days in the Latvian Registry. If the account holder does not react by cancelling the EECS GOs or transferring (selling) the EECS GOs to someone who then cancels them, then the EECS GOs will expire. No operations will be possible on these EECS GOs. The expired EECS GOs will be used in the calculation of the residual mix.
- E.12.3 The Registry system ensures that expired EECS GOs are not available for transfer as the Registry automatically expires EECS GOs according to Expiry rules E.12.1.
- E.12.4 Account Holders can request for EECS GO issuance up to 12 months from the production period end date. EECS GO are then issued with a shorter expiry period which correspond to end of respective production output (month).

### **E.13 End of Life of EECS Certificates – Withdrawal**

This section must demonstrate compliance with the following EECS Rules:

<b>C5.2.3</b>	<b>C6.1.1</b>	<b>C8.2.1</b>	
---------------	---------------	---------------	--

- E.13.1 Withdrawal is removal of a EECS GO from circulation to correct an error. EECS Certificates which have been withdrawn are no longer valid for transfer.
- E.13.2 AST may withdraw a EECS GOs held in an Account on its Registry at the request of the Account Holder of that Account, or otherwise in accordance with the provisions of the EECS scheme as described in section E.10.

## F ISSUER'S AGENTS

### F.1 Production Auditor

This section must demonstrate compliance with the following EECS Rules:

None directly			
---------------	--	--	--

- F.1.1 The Production Auditor verifies and approves information which is provided in forms (Annex 3, Annex 4 and Annex 5). In cases where the installed capacity of the electricity production facility is below 50 kilowatts, approval by a Production Auditor is not required for the completion of Annex 3. Production Auditors use industry best practices and also include on-site inspection. Charges for Production Device services are concluded based on mutual agreement. AST has no responsibility in relation to Production Auditor charges for services. Requirements and link to the list of the Production Auditors is available in Annex 1. See section D.3.4. for details regarding audit practise.
- F.1.2 Production Registrar
- F.1.3 AST acts as the Production Registrar and is responsible for assessing applications to register Production Devices for the purposes of the relevant EECS Product and National Law.

### F.2 Measurement Body(/ies)

This section demonstrates compliance with the following EECS Rules:

H			
---	--	--	--

- F.2.1 Measurement bodies role is described in B.3.3 and their functions in Latvia Domain described under section E.4.

## G ACTIVITY REPORTING

### G.1 Public Reports

This section demonstrates compliance with the following EECS Rules:

E3.3.4	HPA section 14.2		
--------	------------------	--	--

- G.1.1 AST is obligated by National Law to publish on its website link <https://www.ast.lv/en/content/guarantees-origin>, no later than 30 calendar days from the end of a calendar month, information on the <http://cmo.grexel.com/Lists/PublicPages/Statistics.aspx>:
- G.1.1.1 The Quantities (in MWh) of electricity produced in Latvia from renewable energy sources, electricity produced from high efficient cogeneration and supplied to the electricity grids for which EECS GOs have been issued, for the past calendar month, shown according to the types of energy sources;
- G.1.1.2 Each month in the Registry public statistics<sup>1</sup> will be published EECS GO transaction statistics for Latvia domain in previous month. Publication include following items (data items are published in total and divided to the types of energy sources):
- G.1.1.2.1 Amount of issued EECS GOs;
- G.1.1.2.2 Amount of cancelled EECS GOs;
- G.1.1.2.3 Amount of imported EECS GOs;
- G.1.1.2.4 Amount of exported EECS GOs;
- G.1.1.2.5 Amount of internally transferred EECS GOs;
- G.1.1.2.6 Amount of expired EECS GOs.
- G.1.1.3 Recognition of the EECS GOs issued by other AIB Members and transfers and use of the EECS GOs, shown according to the types of energy sources.
- G.1.2 AST, no less than once every three months, will make available to the Secretary General of AIB, the number of Scheme Certificates with respect to each EECS Product, within the preceding three calendar months
- G.1.3 AST ensures the confidentiality of the information provided by the EECS Market Participants and compliance with personal data legal protection requirements in the publication of all information.

### G.2 Record Retention

This section demonstrates compliance with the following EECS Rules:

A12.1.1	C5.1.2	D8.1.2	
---------	--------	--------	--

- G.2.1 AST shall retain all records to which it has had access to, relating to any EECS GOs on its Registry for no less than 10 years after its Cancellation or Expiry or for a period that may be required by applicable national legislation.

### G.3 Orderly Market Reporting

This section demonstrates compliance with the following EECS Rules:

E4.2.5	E4.2.6	E4.2.7	

- G.3.1 AST will inform the AIB of any relevant changes in legislation regarding the EECS scheme in Latvia, especially if it involves changes to this Domain Protocol.
- G.3.2 AST will enforce the rules in relation to any act of non-compliance. AST will provide all required information to AIB to resolve or investigate such action.
- G.3.3 If AST becomes aware that Account Holders fail to comply with the EECS Product rules to the extent that breaches Competition Law, or any applicable law governing the conduct of financial markets, then AST will report it to relevant Competent Authorities. AST will report to AIB of such incidents to extent that it does not breach its duty of confidentiality to the relevant Account Holder.
- G.3.4 If AST determines that an Account Holder is in breach of the Product Rules or determines that a Production Device does not meet the PD Qualification Criteria for an EECS Product in relation to which it is registered, then AST will:
- G.3.4.1 take action to secure that EECS GO issuance is not done for Production Devices that fail to meet Product Rules and PD qualification Criteria. Such action to include, in a case of material non-compliance by the Account Holder, the withdrawal of registration of the relevant Production Device for the purposes of that EECS Product; and
- G.3.4.2 AST will notify the AIB of such a breach where AST is of the reasonable opinion that such a breach could affect the transfer of EECS GOs from its Registry to the EECS Registration Database of another Member.

## H ASSOCIATION OF ISSUING BODIES

### H.1 Membership

This section demonstrates compliance with the following EECS Rules:

C2.2.6	C2.2.7		
--------	--------	--	--

- H.1.1 The Association of Issuing Bodies brings together the issuing bodies of European energy certificate schemes. The AIB promotes the use of a standardised system, based on a harmonised environment, structures and procedures in order to ensure the reliable operation of European energy certificate systems. With its independent and peer reviews, and its periodic audits, the AIB provides a robust framework for reliable and fraud-resistant GO systems. Among others, it can also act by suspending transfers through the Hub. Membership of AIB facilitates mutual recognition of GOs across Europe.
- H.1.2 In case AST ceases to be a Scheme Member of an EECS Scheme, it shall revise its EECS Registration Database so that every Production Device registered therein ceases to be registered for the purposes of EECS. Certificate issuing under EECS would stop, and EECS GOs would remain tradable only until Expiry.
- H.1.3 In case AST ceases to be the Authorised Issuing Body for EECS GOs, it shall revise its EECS Registration Database so that each Production Device in the Domain ceases to be registered for the purposes of EECS GOs, it shall stop issuing EECS GOs and after a transitional period the registry shall be taken offline.

### H.2 Complaints to the AIB

This section must demonstrate compliance with the following EECS Rules:

None directly	(J1.1.2)		
---------------	----------	--	--

- H.2.1 An Account Holder is allowed to notify the Secretary General of AIB in writing in case:
  - a) an Authorised Issuing Body in relation to an EECS GO is in breach of any of the provisions of Product Rules in relation to EECSGO or
  - b) any Product Rules do not comply with the relevant provisions of the EECS Rules, and evidence is provided substantiating such allegation, and that the Authorised Issuing Body has been given adequate opportunity to respond to such allegation.

The General Secretary of AIB shall invite the relevant Authorised Issuing Body to respond to the allegation.

## I CHANGE CONTROL

### I.1 Complaints to AST

This section must demonstrate compliance with the following EECS Rules:

None directly			
---------------	--	--	--

- I.1.1 AST will endeavour to deal with complaints received via e-mail go@ast.lv as soon as possible and within a period of 20 business days. Treatment of the complaint and disputes will be made in accordance with the national legislation of Latvia.

### I.2 Disputes

This section must demonstrate compliance with the following EECS Rules:

None directly			
---------------	--	--	--

- I.2.1 All disputes and disagreements that may arise shall be resolved by negotiations via e-mail go@ast.lv. If no agreement can be reached within 20 business days, either party shall be entitled to initiate dispute resolution in the Latvian courts.

### I.3 Change Requests

This section demonstrates compliance with the following EECS Rules:

E4.2.3	E6.2.1e	L5.1.1	
--------	---------	--------	--

- I.3.1 An EECS Market Participant may propose a modification to this Domain Protocol.
- I.3.2 Such a proposal should include a detailed description, including an exact specification of any proposed modification of this Domain Protocol and be sent in writing to AST.
- I.3.3 On receipt of such a request, AST will:
- I.3.3.1 Respond to the request describing the procedures to be followed and estimating when a reply is expected;
- I.3.3.2 Consult with the other EECS Market Participants within Latvia and when relevant with other AIB members;
- I.3.3.3 Decide whether the request and its consequences are in its opinion reasonable;
- I.3.3.4 Inform the Participants within Latvia of the outcome of this decision.
- I.3.4 AST may make such modifications to this Domain Protocol as are in its opinion necessary to the effective, transparent and efficient operation of the market.
- I.3.5 Any modifications to this Domain Protocol are subject to approval by the AIB (Assessment Panel in accordance with EECS rules section L5.2.1 and the prior consent of the General Meeting in accordance with the provisions of EECS rules section L5) that such changes do not conflict with the Principles and Rules of Operation of the Association of Issuing Bodies (AIB) for The European Energy Certification Registry.

- 
- I.3.6 Implementation of modifications will be sent by e-mail to the Participants and will take effect on publication of the documentation on the website [www.aib-net.org](http://www.aib-net.org) and AST <https://www.ast.lv/en/content/guarantees-origin>

## ANNEX 1 CONTACTS LIST

## AUTHORISED ISSUING BODY/REGISTRY OPERATOR

Company name	AS "Augstsprieguma tīkls"
Contact person	Aigars Sīlis
Department	Market Surveillance and Data Analysis Group
Address	86 Darzciema str.
Phone number	(+371) 67728353
E-mail address	go@ast.lv
Website	www.ast.lv

## REGISTRY SUPPORT

Company name	AS "Augstsprieguma tīkls"
Contact person	Aigars Sīlis
Department	Market Surveillance and Data Analysis Group
Address	86 Darzciema str.
Phone number	(+371) 67728353
E-mail address	go@ast.lv
Website	www.ast.lv

 COMPETENT AUTHORITY FOR SUPERVISION OF DISCLOSURE OF THE ORIGIN  
 OF ENERGY

Company name	
Contact person	
Department	
Address	
Phone number	
E-mail address	
Website	

## Production Auditors

A Production Auditor can be:

- an auditor that has valid accreditation issued from the Latvian National Accreditation Bureau (LATAK) in the field of " Pārdotās lietderīgās vai efektīvi izlietotās siltumenerģijas, kas iegūta, ražojot elektroenerģiju koģenerācijā, izmantojot dabas gāzi vai atjaunojamos energoresursus, gada pārskata inspīcēšana"(up until 01.09.2022.) and after accreditation  
"Datu atbilstības apstiprināšana Latvijas elektroenerģijas izcelsmes apliecinājumu

---

*sistēmai". A list of possible Production Auditors is available on the LATAK website [www.latak.gov.lv/](http://www.latak.gov.lv/);*

- the State Environmental Service of Latvia (hereinafter – VVD), a state authority under the supervision of the Ministry of Climate and Energy website <https://www.vvd.gov.lv/lv>

#### Measurement Bodies

- The Authorised Measurement Bodies are transmission and distribution system operators that are listed on The Public Utilities Commission website [www.sprk.gov.lv](http://www.sprk.gov.lv)

## ANNEX 2 ACCOUNT APPLICATION/AMENDMENT FORM

<b>Account</b>	
Application purpose	<input type="checkbox"/> New account <input type="checkbox"/> Amend account <input type="checkbox"/> De-register account
Company Name/name, surname	
VAT code(Business ID)/Person ID	
Legal address / registered residence (country, city, street, postal code)	
Organization type	<input type="checkbox"/> Electricity Producer <input type="checkbox"/> Electricity Supplier <input type="checkbox"/> GO Trader
If the Account Holder is not responsible for payment obligations, please indicate the individual or legal entity that will assume responsibility.*	Company: _____ Registration number: _____ VAT payer number: _____ Legal address: _____ Bank code: _____ Account number: _____ E-mail: _____ Signatory's position: _____
Trading Scheme	EECS GO
<b>Account Holder Root user</b>	
Action	<input type="checkbox"/> New Root user <input type="checkbox"/> Amend existing Root user
User name	
User surname	
User e-mail	
User mobile phone	

---

Applicant Signature\*\*

Date\*\*

(\* By selecting this field, both the Account Holder and the third party assuming payment responsibility will receive a supplementary agreement via email. This agreement must be signed by all three parties. If this field is later updated and the form is resubmitted, no auditor approval is required for the change of this specific information.)

(\*\* if the document is signed with a secure electronic signature, see the Applicant's signature in the electronic signature, as well as the date in the time stamp of the document signature)

## ANNEX 3 PRODUCTION DEVICE REGISTRATION/AMENDMENT FORM

Account Holder	
Account Holder name	
Account Holder VAT code (Business ID)/Person ID:	
Is the Account Holder also the owner of the Production Device?	<input type="checkbox"/> Yes <input type="checkbox"/> No
Production Device	
Application purpose:	<input type="checkbox"/> New Production Device <input type="checkbox"/> Amend Production Device <input type="checkbox"/> De-register Production Device
Production Device (object) name:	
Capacity specified in the system operator's permit (kW)	
Address of Production Device (Country, City, Street, Postal code)	
Coordinates (longitude, latitude)	
The first date of commissioning	
Grid connection	<input type="checkbox"/> TSOs grid <input type="checkbox"/> DSOs grid _____ (name)
Metering ID:  <b>For TSO network:</b> Object EIC (example: 43ZAST1111111111)  <b>For DSO network:</b> Object EIC and Metering Point code (example: 43Z- STO11111111, 12345678)	
Auxiliary production equipment (if applicable,	<input type="checkbox"/> Yes <input type="checkbox"/> No

please provide detailed information)			
If the production device is not directly connected to the grid, please specify the circumstances and provide the additional relevant meter registration numbers:			
Does the production device include an integrated Battery Energy Storage System (BESS)?	<input type="checkbox"/> Yes <input type="checkbox"/> No		
Is the integrated Battery Energy Storage System (BESS) exclusively connected to this Production Device?	<input type="checkbox"/> Yes <input type="checkbox"/> No		
Permission date to connect the Battery Energy Storage System for a testing period.			
Fuel (-s)*	Level 1		
Fuel (-s)* Technology*		Level 2	Level 3
	Level 1		
Technology*  If you wish the Production Device information to be published on the AST website, please provide the e-mail address and phone number of the responsible person.		Level 2	Level 3
Account Holder who receives issued EECS GO (Account Holder name and Business ID) (optional – fill in case differs from Account Holder from above)**			
Trading Scheme	EECS GO		

--	--

(\*For fuel and technology input please see EECS Rules Fact Sheet 5 "TYPES OF ENERGY INPUTS AND TECHNOLOGIES"(<https://www.aib-net.org/eeecs/fact-sheets>))

(\*\* If this field is later updated and the form is resubmitted, no auditor approval is required for the change of this specific information.)

The State aid					
Production Device received Investment support			<input type="checkbox"/> Yes or <input type="checkbox"/> No If Yes, fill the table below		
Production Device receives Production support			<input type="checkbox"/> Yes or <input type="checkbox"/> No If Yes, fill the table below		
Governor of Support scheme	Support scheme type (Production/ Investment support)	Purpose of the State aid	Support scheme number	Tool	Amount, EUR (In case of Investment support)

Account Holder Signature\*\*\*

Date\*\*\*

Production Auditor (Registrar) Signature\*\*\*

Date\*\*\*

(\*\*\* if the document is signed with a secure electronic signature, see the signatures in the electronic signature, as well as the dates in the time stamp of the document signature)

## ANNEX 4 HIGH EFFICIENCY COGENERATION DECLARATION

Account Holder	
Account Holder VAT code (Business ID)/Person ID:	
Production Device name:	
Production Device GSRN <sup>No</sup>	
Production period	
Generated electricity volume (MWh) <sup>CHP GO</sup>	
Primary Energy Savings (MJ/MWh)* <sup>CHP GO</sup>	
Primary Energy Savings (%)*	
Overall Primary Energy Savings (%) <sup>CHP GO</sup>	
Generated Heat (MWh)*	
Use of Heat*	<input type="checkbox"/> Heating, including district heating and Cooling <input type="checkbox"/> Industrial use, including process heating <input type="checkbox"/> Agricultural use
Lower Calorific Value (MJ/kg, m3 or l)*	
Production Device operational electrical energy generation efficiency (%)* <sup>CHP GO</sup>	
Production Device operational thermal energy generation efficiency(%)* <sup>CHP GO</sup>	
CO <sub>2</sub> Saved (kg/MWh) <sup>CHP GO</sup>	
CO <sub>2</sub> Emissions (kg/MWh) <sup>CHP GO</sup>	
Thermal Capacity (MW)	
Trading Scheme	EECS GO

<sup>No</sup> Number automatically assigned in the Registry at the time of registration of the Production Device, for example, 643002406731001111;

\*Parameters set by Electricity Market law, that has to be defined particularly for high efficiency cogeneration;

<sup>CHP GO</sup> The result of the calculation of the cogeneration calculator ([chp-go.tso.lv](http://chp-go.tso.lv)) developed by AIB (Association of Issuing Bodies).

Account Holder Signature

Date

Production Auditor Signature

Date

(\*\* if the document is signed with a secure electronic signature, see the signatures in the electronic signature, as well as the dates in the time stamp of the document signature)

## ANNEX 5 DECLARATION FOR THE MIXED-FUEL PRODUCTION DEVICES

Account Holder	
Account Holder VAT code (Business ID)/Person ID	
Production Device name	
Production Device GSRN*	
Production period	
Total net generation in period (MWh)	
Share of net generation in production period from fuel (please specify for all fuel(s)), %:	
Share	Fuel ( <i>For combustible fuel specify mass of the relevant fuel and its average calorific value</i> )

\*Number automatically assigned in the Registry at the time of registration of the Production Device, for example, 643002406731001111.

Account Holder Signature\*\*

Date\*\*

Production Auditor Signature\*\*

Date\*\*

(\*\*) if the document is signed with a secure electronic signature, see the signatures in the electronic signature, as well as the dates in the time stamp of the document signature)

---

**ANNEX 6 APPROVAL FORM**

I certify that the criteria for high efficiency cogeneration were not met during the specified production period.

Account Holder name	
Account Holder VAT code (Business ID)/Person ID	
Production device name	
Production period	
Primary energy savings (MJ/MWh)	
Primary energy savings (%)*	

\*Parameter set by Electricity Market Law

---

**Account Holder Signature\*\***

---

**Date\*\***

(\*\*) if the document is signed with a secure electronic signature, see the signature in the electronic signature, as well as the date in the time stamp of the document signature)

---

## ANNEX 7 EECS CANCELLATION STATEMENT



### Cancellation Statement

This cancellation statement acts as a receipt for the certificates listed below and for the purpose shown. With this Cancellation Statement, released on the Transaction Date, the indicated certificates are no longer tradable. Onward sale of this Cancellation Statement is prohibited. The environmental qualities of the associated energy have been consumed and this Cancellation Statement and these certificates may not be transferred to any party other than the energy supplier or end-consumer specified below.

### Transaction details

Transaction Type:

Transaction Date:

Transaction Number:

Message to Receiver:

From	To
Account Holder:	Name of Beneficiary:
Account:	Cancellation Purpose:
Domain:	Consumption Period:
Street:	Country of Consumption:
Postal Code and City:	Location of Beneficiary:
Country:	Usage Category:
	Type of Beneficiary:

### Total

Total MWh:

Total GO:

Certificate Number (From - To)	Volume	Domain	Fuel, Technology	S/T	Issuing Date	Production Period	Production Device (GSRN, installed capacity, name)	Trading Schemes	Support

Production Device public information

Production Device Name:

Production Device GSRN:

Domain of Production Device:

Installed Capacity, MW:

Date of Commissioning:

Location of Production Device:

Technology:

Fuel:

Investment support:

Production support:

CO2 Saved(kg/MWh):

Primary Energy Savings(MJ/MWh):

Primary Energy Savings(%):

Use of Heat Code:

Lower Calorific Value(MJ/kg, m3 or l):

CO2 Emissions(kg/MWh):

Thermal Capacity(MW):

Mechanical Capacity(MW):

Overall Primary Energy Savings(%):

Useful Cogeneration Heat(GJ/MWh):

Electrical Efficiency(%):

Thermal Efficiency(%):

## ANNEX 8 EECS GO VIEW IN THE REGISTRY

### Transaction details

Transaction Type:	Issue
Transaction Date:	2020-09-21 13:37:01
Transaction Number:	2020092100002
Message to Receiver:	-

### From

Issuing Body:	<a href="#">AS AUGSTSPRIEGUMA TIJKS</a>
Domain:	Demo Latvia
Street:	Latvian demo street
Postal Code and City:	00000 Latvian demo city
Country:	Latvia

### To

Account Holder:	<a href="#">Tests</a>
Account:	LV- Tests- 643002406771001272
Domain:	Demo Latvia
Street:	Demo iela
Postal Code and City:	LV-1111 Riga
Country:	Latvia

### Total

Total MWh:	50
Total GO:	50

Certificate  
Number (From -  
To)  
6430024065590  
25100000004399  
90  
To  
6430024065590  
25100000004400  
39

Volume	Domain	Fuel, Technology	S/T	Issuing Date	Production Period	Production Device (GSRN, installed capacity, name)	Trading Schemes	Support Schemes
50	Demo Latvia	F0100000, T030000	T	2020-09-21	2020-09-01 To 2020-09-31	643002406731000222 20 MW Part_Issue	GO	Investment and production support

### Production Device public information

Production Device Name:	Part_Issue
Production Device GSRN:	643002406731000222
Domain of Production Device:	Demo Latvia
Installed Capacity, MW:	20
Date of Commissioning:	2020-01-01
Location of Production Device:	LV-1111 Riga, LV
Technology:	T030000 - Hydropower
Fuel:	F01000000 - Renewable
Investment support:	Tools, etc.
Production support:	Tools, etc.
CO2 Saved(kg/MWh):	10
Primary Energy Savings(MJ/MWh):	10
Primary Energy Savings(%):	10
Use of Heat Code:	Heating, including District Heating and Cooling
Lower Calorific Value(MJ/kg, m3 or l):	10
CO2 Emissions(kg/MWh):	10
Thermal Capacity(MW):	10
Mechanical Capacity(MW):	10
Overall Primary Energy Savings(%):	10
Useful Cogeneration Heat(GJ/MWh):	10
Electrical Efficiency(%):	10
Thermal Efficiency(%):	10